

MAGMATIC PRISMA DRIVER 8IP

DMX CHANNEL FUNCTIONS & VALUES

Magmatic Prisma Driver 8IP: DMX Channels / Functions				
Supports Software Versions: 1.01				
CHANNEL			DMX VALUE	FUNCTION
8-CH	9-CH	12-CH Ext		
1	1	1	000 - 255	LED Signal Output 1
2	2	2	000 - 255	LED Signal Output 2
3	3	3	000 - 255	LED Signal Output 3
4	4	4	000 - 255	LED Signal Output 4
5	5	5	000 - 255	LED Signal Output 5
6	6	6	000 - 255	LED Signal Output 6
7	7	7	000 - 255	LED Signal Output 7
8	8	8	000 - 255	LED Signal Output 8
		9	000 - 255	Master Dimmer
		10	000 - 255	Dimmer Fine
		11		Strobe
			000 - 031	Closed
			032 - 063	Open
			064 - 095	Strobe, slow to fast
			096 - 127	Open
			128 - 159	Pulse, slow to fast
			160 - 191	Open
			192 - 223	Random Strobe, slow to fast
		224 - 255	Open	
	9	12		Dim Mode
			000 - 020	Standard
			021 - 040	Stage
			041 - 060	TV
			061 - 080	Architectural
			081 - 100	Theatre
			101 - 120	Stage 2
				Dimmer Delay Time
			121	0.0 s
			122	0.1 s
	123	0.2 s		

CONTINUED ON NEXT PAGE

MAGMATIC PRISMA DRIVER 8IP

DMX CHANNEL FUNCTIONS & VALUES

Magmatic Prisma Driver 8IP: DMX Channels / Functions				
Supports Software Versions: 1.01				
CHANNEL			DMX VALUE	FUNCTION
8-CH	9-CH	12-CH Ext		
				Dimmer Delay Time (continued)
			124	0.3 s
			125	0.4 s
			126	0.5 s
			127	0.6 s
			128	0.7 s
			129	0.8 s
			130	0.9 s
			131	1.0 s
			132	1.5 s
			133	2.0 s
			134	3.0 s
			135	4.0 s
			136	5.0 s
			137	6.0 s
			138	7.0 s
			139	8.0 s
			140	9.0 s
			141	10.0 s
			132 - 255	Default (0.1 s)