

# grandMA3 I/O Node

Art.-No. 4023577



The grandMA3 I/O Node is the multi-tool of signal distribution within a grandMA3 lighting control system. Wherever the signal is generated or needed – just place a grandMA3 I/O Node there and receive or send external signals.

The grandMA3 I/O Node comes in the same housing as a grandMA3 2/4 Port Node and is also available as PoE variant (Power over Ethernet).

The display shows the status of all input and output signals. Just add the grandMA3 I/O Node as a Session Member and it is ready to go.

It has never been easier to integrate external signal flows into the MA-Net workflow. Once a grandMA3 I/O Node receives MIDI, Timecode or DC Remote signals, these are available immediately throughout the grandMA3 lighting control system, and can be used in any grandMA3 onPC or console. The same is true for transmitting MIDI or Timecode signals.

Just add a grandMA3 I/O Node and connect locally with external signals to integrate them into the MA-Net3 workflow.

## Scope of delivery

Art.-No.	Article	Quantity
4025836	MA Quick Manual for grandMA3 I/O Nodes	1

1x powerCON TRUE1 socket (NAC3FX-W-TOP) or similar

## Technical Specifications

<b>Parameters</b>	none
<b>Parameters Mode2</b>	none
<b>Operating voltage/ Supply voltage</b>	AC 100 - 240 V; 50/60 Hz
<b>Power</b>	max. 15 VA
<b>Operating Temperature</b>	0 °C up to 40 °C / 32 °F up to 104 °F
<b>Dimensions</b>	207 x 184 x 43 mm / 9 x 8 x 2 in (width x depth x height)
<b>Net weight</b>	2 kg / 5 lbs
<b>Connectors</b>	1 x powerCON TRUE1 1 x etherCON/RJ45 1 x MIDI In (5pin DIN female) 1 x MIDI Out (5pin DIN female) 1 x Linear Timecode (3pin XLR female) 1 x GPI General Purpose Interface (D-SUB DE9 female) for remote control 1 x USB 2.0 (type A)

## Article

Art.-No.	Article
4023577	grandMA3 I/O Node

## Accessories

Art.-No.	Article
130281	MA 2Port Node / 4Port Node 19" rack mounting kit - blank panel
130283	MA 2Port Node / 4Port Node 19" rack mounting kit - 2x Nodes
130284	MA 2Port / 4Port / 8Port Node rigging plate

## More product pictures

