



Configuration:

LWR-1050-A0-P1 (North America)

LWR-1050-E0-P1 (European Union, United Kingdom)

LWR-1050-Z0-P1 (Australia, New Zealand)

Product Overview:

This convenient package includes a Wi-Fi Audio Receiver, Ear Speaker, Lanyard, plus an Advanced Neck Loop for telecoil equipped hearing aids.

The ListenWIFI Audio Receiver is a state-of-the-art assistive listening receiver, allowing venues to provide hearing assistance to guests while meeting compliance with disability and accessibility requirements. Real-time audio is streamed from a ListenWIFI Audio Server over the Wi-Fi network directly to LWR-1050 receivers. Venues can simply lend receivers to guests who want to hear the audio loud and clear. Experience great quality audio and industry-leading low latency audio at your venue with the ListenWIFI Audio Receiver.

The LWR-1050 is the most automated receiver available, automatically triggering to a channel based on the device's location (using Listen Beacons). Provide guests with a completely automated solution when 2 or more channels are available, ensuring guests are listening to the right channel in the right location.

Wi-Fi Audio Receivers are also beneficial for venues who would rather manage and check out dedicated hearing assistance devices, thus avoiding the hassle associated with supporting personal smartphones. Simply plug in wired headphones to listen or an inductive neck loop for use with hearing aids equipped with a T-Coil.

From classrooms to houses of worship, theatres and more, the LWR-1050 Wi-Fi Audio Receiver is an excellent assistive listening choice.

Highlights:

- Package includes Receiver, Ear Speaker, Lanyard, and Neck Loop
- Dedicated Wi-Fi Audio Receiver for assistive listening and language translation
- Meets ADA and worldwide disability compliance (DDA, IBC, CBC, etc.)
- Dedicated devices for venues where personal smartphones are not allowed
- Backup devices for venues who want to avoid the hassle of supporting personal smartphones
- Extremely easy for guests to use
- Automatically connects to proper channel based on location (with [LA-490](#) beacons)
- Superior audio performance & Industry-leading latency
- Great quality and reliability
- Compatible with standard earbuds & headphones (CTIA compliant)
- Compatible with hearing aid telecoils with optional Neck Loop (LA-438)
- Field Replaceable lithium-ion rechargeable batteries
- Easy setup, management, and tracking using ListenWIFI Manager for Windows®

Includes:

One (1) LWR-1050 Wi-Fi Audio Receiver One (1) LA-365 Rechargeable Li-ion Battery One (1) LA-164 Ear Speaker One (1) LA-445 Breakaway Lanyard One (1) LA-438 Advanced Neck Loop (Adult) One (1) Quick Start Guide

Product Specification: ListenWIFI Wi-Fi Audio Receiver (Package 1) (COMING SOON)	
Physical	
Dimensions (H x W x D) with Belt Clip	10 x 5.4 x 2.4 cm (3.93 x 2.13 W x 0.93 in.)
Unit Dimensions (H x W x D)	10 x 5.4 x 1.6 cm (3.93 x 2.13 W x 0.63 in.)
Unit Weight	80 g (2.82 oz.)
Shipping Weight	105 g (3.7 oz.)
Enclosure material	PC plastic (IR transparent)
Display	31 x 16 mm (1.22 x .63 in) , 64 x 128 pixel OLED display
LED	Multi-colored, multi-function
Light Sensor	Visible light, automatically adjusts display brightness
Color	Black, Chrome Buttons
User Controls	Volume up/down, channel up/down, language selection, power, status
Headphone Connection	3.5mm (1/8") headphone jack, TRRS, CTIA compliant
USB Connection	USB-Micro for charging and programming
Dock Connection	4 contacts w/ magnetic latch for charging and programming via docking station
Belt Clip	Removable and Reversible
Battery Door	Removable for battery replacement
Audio	
Audio Output Method	3.5mm connection for wired headphones or inductive neck loops
Frequency Response (system)	20 Hz - 20 kHz \pm 1dB (at nominal level)
Distortion (system)	< 1% Total Harmonic Distortion (at nominal level)
Signal to Noise Ratio (system)	> 74 dB (at nominal level)
Dynamic Range (system)	86 dB (at maximum level)
Latency (system)	40-60 mS, dependent on network, traffic, and QOS
Communications	
Wi-Fi Bands	802.11 a/b/g/n (2.4 and 5 GHz)
Wi-Fi Frequencies	2.4 GHz Channels: 1,2,3,4,5,6,7,8,9,10,11 5 GHz Channels: 36,40,44,48,52,56,60,64,100,104,108,112,116,120*,124*,128*,132,136,149,153,157,161,165
	*Channels not available in North American variant (A0)
Bluetooth	5.0
USB	2.0
Audio	125 kbps for audio streaming
Security	TLS 1.2 (AES 128 bit)
Infrared (IR)	Protocol: SyncLink IR, 850nM
Controls	
User Controls	Power on/off, display on/off, channel selection, volume up/down, language selection
Setup/Programming	Via Manager Software and USB port on receiver Via Manager Software and USB

Product Specification: ListenWIFI Wi-Fi Audio Receiver (Package 1) (COMING SOON)	
	port on Docking Station Directly in Docking Station using the clone operation
Channel Triggering	Automatic via SyncLink Infrared (IR) when in proximity to LA-490 beacons.
Indicators	
Display	Channel playing, available channels, battery level with time remaining, Wi-Fi signal strength, volume status, charging status, language selection, profile name
LED	Blue flashing - receiver is turning on/booting up
	Red flashing - indicates receiver has not been configured or Wi-Fi is unavailable
	Green flashing - receiver is charging
	Green solid - receiver is fully charged
Power and Charging	
Power Supply	USB-Micro or Docking Station - 5V, 500mA
Battery Type	Lithium - ion, rechargeable, field replaceable
Battery Size	1200 mAh
Battery Life	7 hours of continuous audio streaming
Battery Charge Time	Fully charged in < 4 hours (dead battery)
Power Save Modes	Auto Off - powers down on loss of audio (adjustable OFF, 10, 20, or 30 min)
	Auto Power - powers down/up upon insertion/removal of charger (adjustable ON/OFF)
	Jack Sense - powers down/up upon insertion/removal of headphones (adjustable ON/OFF)
Environmental	
Temperature - Operation	-10 °C (14 °F) to +40 °C (104 °F)
Temperature - Storage	-20 °C (-4 °F) to +50 °C (122 °F)
Relative Humidity	0 to 95% relative humidity, non condensing
Compliance	
Regulatory Marks	FCC, CE, ROHS, UKCA
Warranty	
Receiver Warranty	2 years
	*Specifications are subject to change without notice.