

ADJ COB CANNON LP200 - DMX TRAITS

CHANNEL										DMX VALUE	FUNCTION
5CH	8CH A	8CH B	9CH	10CH A	10CH B	12CH	13CH	16CH	20CH		
1	1		1	1	1	1	1	1	1	000 - 255	Red , 0% to 100%
				2					2	000 - 255	Red Fine
2	2		2	3	2	2	2	2	3	000 - 255	Green , 0% to 100%
				4					4	000 - 255	Green Fine
3	3		3	5	3	3	3	3	5	000 - 255	Blue , 0% to 100%
				6					6	000 - 255	Blue Fine
4	4		4	7	4	4	4	4	7	000 - 255	Amber , 0% to 100%
				8					8	000 - 255	Amber Fine
5	5		5	9	5	5	5	5	9	000 - 255	Lime , 0% to 100%
				10					10	000 - 255	Lime Fine
		1			6	6	6	6	11	000 - 255	Color Macros , please see Color Macros Chart section of this manual
		2	6		7		7	7	12	000 - 255	Color Temperature , 2300K - 9900K linear
											Shutter / Strobe
										000 - 031	LEDs off
										032 - 063	LEDs On
										064 - 095	Strobe Effect, slow to fast
	6	3	7		8	7	8	8	13	096 - 127	LEDs On
										128 - 159	Pulse Effect in Sequences
										160 - 191	LEDs On
										192 - 223	Random Strobe Effect, slow to fast
										224 - 255	LEDs On
	7	4	8		9	8	9	9	14	000 - 255	Dimmer Intensity , 0% to 100%
	8	5	9		10	9	10	10		000 - 255	Dimmer Fine
											Auto Programs
										000 - 010	Off
						10		11	15	011 - 026	Auto Program 1
										027 - 043	Auto Program 2
										044 - 060	Auto Program 3
										061 - 076	Auto Program 4

CONTINUED ON NEXT PAGE

ADJ COB CANNON LP200 - DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
5CH	8CH A	8CH B	9CH	10CH A	10CH B	12CH	13CH	16CH	20CH		
						10		11	15		<i>Auto Programs (continued)</i>
										077 - 093	Auto Program 5
										094 - 110	Auto Program 6
										111 - 126	Auto Program 7
										127 - 143	Auto Program 8
										144 - 160	Auto Program 9
										161 - 176	Auto Program 10
										177 - 193	Auto Program 11
										194 - 210	Auto Program 12
										211 - 226	Auto Program 13
										227 - 255	No Function
						11		12	16	000 - 255	<i>Auto Programs Speed, slow to fast</i>
						12		13	17	000 - 255	<i>Auto Programs Fade, least to most</i>
		6					11	14	18		<i>Dim Mode</i>
										000 - 020	Default to unit setting
										021 - 040	Standard
										041 - 060	Stage
										061 - 080	TV
										081 - 100	Architectural
										101 - 120	Theatre
										121 - 140	Stage 2
											<i>Dim Speed</i>
										141	0.1s
										142	0.2s
										143	0.3s
										144	0.4s
										145	0.5s
										146	0.6s
										147	0.7s
										148	0.8s
										149	0.9s
										150	1.0s
										151	1.5s

CONTINUED ON NEXT PAGE

ADJ COB CANNON LP200 - DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
5CH	8CH A	8CH B	9CH	10CH A	10CH B	12CH	13CH	16CH	20CH		
		6					11	14	18		<i>Dim Speed (continued)</i>
										152	2.0s
										153	3.0s
										154	4.0s
										155	5.0s
										156	6.0s
										157	7.0s
										158	8.0s
										159	9.0s
										160	10.0s
										161 - 255	Default to unit setting
		7					12	15	19		<i>Dim Curves</i>
										000 - 020	Square
										021 - 040	Linear
										041 - 060	Inv. Squa.
										061 - 080	S. Curve
										081 - 255	No function
		8					13	16	20		<i>Refresh Rates</i>
										000 - 015	Default to unit setting
										016 - 030	900 Hz
										031 - 045	1000 Hz
										046 - 060	1100 Hz
										061 - 075	1200 Hz
										076 - 090	1300 Hz
										091 - 105	1400 Hz
										106 - 120	1500 Hz
										121 - 135	2500 Hz
										136 - 150	4000 Hz
										151 - 165	5000 Hz
										166 - 180	10,000 Hz
										181 - 195	15,000 Hz
										196 - 210	20,000 Hz
										211 - 225	25,000 Hz
										226 - 255	No function