

## ADJ ENCORE LP5IP - DMX TRAITS

CHANNEL						DMX VALUE	FUNCTION
4CH	7CH	8CH	10CH	13CH	16CH		
1	1	1	1	1	1	000 - 255	<b>Red</b> , 0% - 100%
		2				000 - 255	<b>Red Fine</b>
2	2	3	2	2	2	000 - 255	<b>Green</b> , 0% - 100%
		4				000 - 255	<b>Green Fine</b>
3	3	5	3	3	3	000 - 255	<b>Blue</b> , 0% - 100%
		6				000 - 255	<b>Blue Fine</b>
4	4	7	4	4	4	000 - 255	<b>Lime</b> , 0% - 100%
		8				000 - 255	<b>Lime Fine</b>
			5	5	5	000 - 255	<b>Color Macros</b> , see <b>Color Macros Chart</b> section for detailed information
			6	6	6	000 - 255	<b>Color Temperature</b> , 2700K - 7000K Linear
							<b>Color Temperature Macros</b>
						000	Off
			7	7	7	001 - 054	2700K
						055 - 109	3200K
						110 - 164	4000K
						165 - 219	5600K
						220 - 255	6500K
							<b>Shutter, Strobe</b>
						000 - 031	LEDs Off
						032 - 063	LEDs On
						064 - 095	Strobe effect, slow to fast
	5		8	8	8	096 - 127	LEDs On
						128 - 159	Pulse-effect in sequences
						160 - 191	LEDs On
						192 - 223	Random strobe effect, slow to fast
						224 - 255	LEDs On
	6		9	9	9	000 - 255	<b>Dimmer Intensity</b> , 0% - 100%
	7		10	10	10	000 - 255	<b>Dimmer Fine</b>
							<b>Auto Programs</b>
					11	000 - 031	Off
						032 - 063	Auto Program 1
						064 - 095	Auto Program 2
						096 - 127	Auto Program 3
						128 - 159	Auto Program 4

CONTINUED ON NEXT PAGE

## ADJ ENCORE LP5IP - DMX TRAITS

CHANNEL						DMX VALUE	FUNCTION	
4CH	7CH	8CH	10CH	13CH	16CH			
					11		<b><i>Auto Programs (continued)</i></b>	
						160 - 191	Auto Program 5	
						192 - 223	Auto Program 6	
						224 - 255	Auto Program 7	
					12	000 - 255	<b><i>Auto Program Speed</i></b> , slow to fast	
					13	000 - 255	<b><i>Auto Program Fade</i></b> , least to most	
				11	14		<b><i>Dim Mode</i></b>	
							000 - 020	Default to unit setting
							021 - 040	Standard
							041 - 060	Stage
							061 - 080	TV
							081 - 100	Architectural
							101 - 120	Theatre
							121 - 140	Stage 2
							141	0.1s dim speed
							142	0.2s dim speed
							143	0.3s dim speed
							144	0.4s dim speed
							145	0.5s dim speed
							146	10.6s dim speed
							147	0.7s dim speed
							148	0.8s dim speed
							149	0.9s dim speed
							150	1.0s dim speed
							151	1.5s dim speed
							152	2.0s dim speed
							153	3.0s dim speed
							154	4.0s dim speed
							155	5.0s dim speed
							156	6.0s dim speed
							157	7.0s dim speed
							158	8.0s dim speed
					159	9.0s dim speed		
					160	10.0s dim speed		
					161 - 255	Default to unit setting		

CONTINUED ON NEXT PAGE

## ADJ ENCORE LP5IP - DMX TRAITS

CHANNEL						DMX VALUE	FUNCTION
4CH	7CH	8CH	10CH	13CH	16CH		
				12	15		<b><i>Dim Curves</i></b>
						000 - 020	Square
						021 - 040	Linear
						041 - 060	Inv. Squa
						061 - 080	S. Curve
						081 - 255	No function
				13	16		<b><i>Refresh Rate</i></b>
						000 - 015	Default to Unit Setting
						016 - 030	900 Hz
						031 - 045	1000 Hz
						046 - 060	1100 Hz
						061 - 075	1200 Hz
						076 - 090	1300 Hz
						091 - 105	1400 Hz
						106 - 120	1500 Hz
						121 - 135	2500 Hz
						136 - 150	4000 Hz
						151 - 165	5000 Hz
						166 - 180	10000 Hz
						181 - 195	15000 Hz
				196 - 210	20000 Hz		
				211 - 225	25000 Hz		
				226 - 255	No Function		