

## ELATION PIXEL DRIVER 170IP - DMX TRAITS

CHANNEL		PIXEL NO.	DMX VALUE	FUNCTION
LED Tape	Pixel Wash 40IP			
1	1	1	000 - 255	<b>Red, 0% - 100%</b>
2	2		000 - 255	<b>Green, 0% - 100%</b>
3	3		000 - 255	<b>Blue, 0% - 100%</b>
	4		000 - 255	<b>White, 0% - 100%</b>
4	5	2	000 - 255	<b>Red, 0% - 100%</b>
5	6		000 - 255	<b>Green, 0% - 100%</b>
6	7		000 - 255	<b>Blue, 0% - 100%</b>
	8		000 - 255	<b>White, 0% - 100%</b>
7	9	3	000 - 255	<b>Red, 0% - 100%</b>
8	10		000 - 255	<b>Green, 0% - 100%</b>
9	11		000 - 255	<b>Blue, 0% - 100%</b>
	12		000 - 255	<b>White, 0% - 100%</b>
...	...	...	...	...
118	157	40	000 - 255	<b>Red, 0% - 100%</b>
119	158		000 - 255	<b>Green, 0% - 100%</b>
120	159		000 - 255	<b>Blue, 0% - 100%</b>
	160		000 - 255	<b>White, 0% - 100%</b>
121		41	000 - 255	<b>Red, 0% - 100%</b>
122			000 - 255	<b>Green, 0% - 100%</b>
123			000 - 255	<b>Blue, 0% - 100%</b>
...		...	...	...
508		170	000 - 255	<b>Red, 0% - 100%</b>
509			000 - 255	<b>Green, 0% - 100%</b>
510			000 - 255	<b>Blue, 0% - 100%</b>

**Note:**

- In LED Tape mode, the DMX channel control will vary depending on the set pixel count. 3 RGB control channels will be added for each additional pixel. Up to 170 pixels (510 DMX channels) can be controlled with each Pixel Driver 170IP device.
- In Pixel Wash 40IP mode, the DMX channel control will vary depending on the set pixel count. 4 RGBW control channels will be added for each additional pixel. Up to 40 pixels (160 DMX channels) can be controlled with each Pixel Driver 170IP device.