



### Product Overview:

LA-112 RG-58 50 Ohm Coaxial Cable is best used when more distance is needed for the antennas to have better coverage. Measured at 500 ft. Recommended for coaxial runs less than 100 ft. (30.5 m) at 72 MHz or 50 ft. (15.24 m) at 216 MHz. Signal loss for 72 MHz is 2 dB per 50 ft. Signal loss for 216 MHz is 4 dB per 50 ft.

### Highlights:

- Furthers antenna location



**WARNING:** This product can expose you to chemicals including DIDP, which is known to the State of California to cause cancer. For more information, go to [www.P65Warning.ca.gov](http://www.P65Warning.ca.gov)

### Includes:

LA-112 RG-58 50 Ohm Coaxial Cable (500 ft)

Product Specification: RG-58 50 Ohm Coaxial Cable (500 ft)	
<b>RF</b>	
Attenuation	2 dB per 50 ft. on 72 MHz, 4 dB per 50 ft. on 216 MHz
<b>Physical</b>	
Material	Polyethylene Insulation, PVC Jacket, tinned copper conductor, tinned copper braided shield
Shipping Weight	4 lbs. (1.81 kg) per 100 ft.
Diameter	Outer: .192 in. (4.88 mm), Inner: .116 in. (2.95 mm)
Unit Weight	3.5 lbs. (1.6 0 kg) per 100 ft.
Cable Type	RG-58/U 50 Ohm