

DMX CHANNEL'S FUNCTIONS AND THEIR VALUES (150 DMX CHANNELS) - V1


Mode/Channel				Function	Value	Default Value
Ba	Std	Ext Ring	Ext Pixel			
1	1	1	1	PAN Movement 8bit	0-255	128
2	2	2	2	Pan Fine 16bit: Fine control of Pan movement	0-255	0
3	3	3	3	TILT Movement 8bit	0-255	128
4	4	4	4	Tilt Fine 16bit: Fine control of Tilt movement	0-255	0
5	5	5	5	Speed Fan/Tilt Movement	Max to min speed	0
					Blackout by movement	
					Reserved	
6	6	6	6	Reserved	0-255	
7	7	7	7	Reserved	0-255	
8	8	8	8	Red LED-All Arrays / Background Colour When Chase ON: Red (0-Black, 255-100% Red)	0-255	255
9	9	9	9	Red Fine Led-All Arrays / Background Colour When Chase ON: Red fine (0-Black, 255-100% Red)	0-255	255
10	10	10	10	Green LED-All Arrays / Background Colour When Chase ON: Green (0-Black, 255-100% Green)	0-255	255
11	11	11	11	Green Fine LED-All Arrays / Background Colour When Chase ON: Green fine (0-Black, 255-100% Green)	0-255	255
12	12	12	12	Blue LED-All Arrays / Background Colour When Chase ON: Blue (0-Black, 255-100% Blue)	0-255	255
13	13	13	13	Blue Fine LED-All Arrays / Background Colour When Chase ON: Blue fine (0-Black, 255-100% Blue)	0-255	255
14	14	14	14	Lime LED-All Arrays / Background Colour When Chase ON: Lime (0-Black, 255-100% Lime)	0-255	255
15	15	15	15	Lime Fine Led-All Arrays / Background Colour When Chase ON: Lime fine (0-Black, 255-100% Lime)	0-255	255
16	16	16	16	Shutter, Strobe	LED turn off	32
					LED turn on	
					Strobe effect slow to fast	
					LED turn on	
					Pulse-effect in sequences	
					LED turn on	
					Random strobe effect slow to fast	
					LED turn on	
17	17	17	17	Dimmer Intensity: Intensity 0 to 100%	0-255	0
18	18	18	18	Dimmer Intensity Fine	0-255	0
19	19	19	19	Linear CTO From 8000 To 2700 K	Head 1 Linear CTO from 8000 to 2500K	0
					RGBL mode	
					6500 K (RGB)	
					8000 K- 2500 K (RGB)	
20	20	20	20	Colour Preset: See Appendix	0-255	0
21	21	21	21	Colour Preset / RGBW Cross Fade	Output controlled by RGBL values	0
					Cross fade between RGBL settings and colours preset channel	
					Output controlled by colour preset values	
22	22	22	22	Between Colour Preset Cross Fade	No fade	0
					Cross fade between 2 Colour presets from 100ms to 5 sec	

Mode/Channel				Function	Value	Default Value
23	23	23	23	Zoom: From small to big	0-255	128
24	24	24	24	Zoom Fine	0-255	0
25	25	25	25	Tint Channel (Plus Minus Green)	No Function	127
					From min minus green to 0	
					0 correction	
					From 0 to plus max green	
26	26	26	26	Reset, Internal Programs	unused	0
					Display Off	
					Display On	
					Display Invert Off	
					Display Invert On	
					Auto fan control mode	
					Stage fan control mode	
					Silence fan control mode	
					Super Silence fan control mode	
					Constant Fans Off	
					Constant Fans On	
					unused	
					Square Law	
					Linear	
					1.2K	
					2.4K	
					16K	
					25K	
					Tungsten lamp simulation 500 W	
					Tungsten lamp simulation 1000 W	
					Tungsten lamp simulation 2500 W	
					Tungsten lamp simulation 5000 W	
					Tungsten lamp simulation off	
					All motor reset	
					P/T motor reset	
					Zoom motor reset	
					Reserved	
					IP from mac off	
					IP from mac on	
					Fog fan off	
					Fog fan auto	
					Fog fan on	
					Reserved	
27	27	27	27	Main LED Chase Patterns	Chase OFF	0
					Chase 1	
					Chase 2	

Mode/Channel				Function	Value	Default Value
27	27	27	Main LED Chase Patterns	Chase 3	20-24	0
				Chase 4	25-29	
				Chase 5	30-34	
				Chase 6	35-39	
				Chase 7	40-44	
				Chase 8	45-49	
				Chase 9	50-54	
				Chase 10	55-59	
				Chase 11	60-64	
				Chase 12	65-69	
				Chase 13	70-74	
				Chase 14	75-79	
				Chase 15	80-84	
				Chase 16	85-89	
				Chase 17	90-94	
				Chase 18	95-99	
				Chase 19	100-104	
				Chase 20	105-109	
				Chase 21	110-114	
				Chase 22	115-119	
				Reserved	120-255	
28	28	28	Main LED Chase Speed	Fast to Slow Backward	0-125	0
				Stop (Speed=0)	126-130	
				Slow to Fast Forward	131-255	
29	29	29	Main LED Chase Fade		0-255	0
30	30	30	Main LED Chase Size: Chase Category		0-255	0
31	31	31	Red Chase Colour: Red (0-Black , 255-100% Red)		0-255	255
32	32	32	Green Chase Colour: Green (0-Black , 255-100% Green)		0-255	255
33	33	33	Blue Chase Colour: Blue (0-Black , 255-100% Blue)		0-255	255
34	34	34	Lime Chase Colour: White (0-Black , 255-100% White)		0-255	255
35	35	35	Dimmer Chase: Intensity (0-Black , 255-100%)		0-255	0
36	36	36	Dimmer Background Chase: Inverted disabled when chase OFF / Intensity (0-100%, 255-0%)		0-255	0
37	37	37	Chase, Strobe	Led turn off	0-31	32
				Led turn on	32-63	
				Strobe effect slow to fast	64-95	
				Led turn on	96-127	
				Pulse-effect in sequences	128-159	
				Led turn on	160-191	
				Random strobe effect slow to fast	192-223	
				Led turn on	22-255	
	38	38	Cross Fade To Pixel/Ring Mode: from RGBW control to PIXEL control		0-255	128

Mode/Channel				Function	Value	Default Value
	39			Red LED-Ring1: Red (0-Black, 255-100% Red)	0-255	0
	40			Green LED-Ring1: Green (0-Black, 255-100% Green)	0-255	0
	41			Blue LED-Ring1: Blue (0-Black, 255-100% Blue)	0-255	0
	42			Lime LED-Ring 1: Lime (0-Black, 255-100% Lime)	0-255	0
	43			Red LED-Ring2: Red (0-Black, 255-100% Red)	0-255	0
	44			Green LED-Ring2: Green (0-Black, 255-100% Green)	0-255	0
	45			Blue LED-Ring2: Blue (0-Black, 255-100% Blue)	0-255	0
	46			Lime LED-Ring2: Lime (0-Black, 255-100% Lime)	0-255	0
	47			Red LED-Ring3: Red (0-Black, 25-100% Lime)	0-255	0
	48			Green LED-Ring3: Green (0-Black, 25-100% Lime)	0-255	0
	49			Blue LED-Ring3: Blue (0-Black, 25-100% Lime)	0-255	0
	50			Lime LED-Ring3: Lime (0-Black, 25-100% Lime)	0-255	0
	39			Red LED-Array1: Red (0-Black , 255-100% Red)	0-255	0
	40			Green LED-Array 1: Green (0-Black , 255-100% Green)	0-255	0
	41			Blue LED-Array 1: Blue (0-Black , 255-100% Blue)	0-255	0
	42			Lime LED-Array 1: Lime (0-Black , 255-100% Lime)	0-255	0
	43			Red LED-Array 2: Red (0-Black , 255-100% Red)	0-255	0
	44			Green LED-Array 2: Green (0-Black , 255-100% Green)	0-255	0
	45			Blue LED-Array 2: Blue (0-Black , 255-100% Blue)	0-255	0
	46			Lime LED-Array 2: Lime (0-Black , 255-100% Lime)	0-255	0
...						
	147			Red LED-Array 28: Red (0-Black , 255-100% Red)	0-255	0
	148			Green LED-Array 28: Green (0-Black , 255-100% Green)	0-255	0
	149			Blue LED-Array 28: Blue (0-Black , 255-100% Blue)	0-255	0
	150			Lime LED-Array 28: Lime (0-Black , 255-100% Lime)	0-255	0

*Errors and omissions for all information given in this DMX chart are possible.
All information is subject to change without prior notice.*



SCAN FOR MORE

www.ayrton.eu



AYRTON
Digital Lighting