



The Superlux PS2B is a two channel phantom Power supply for one or two condenser microphones. It is the perfect solution for applications where the use of condenser microphones is desired and the mixer, recorder, PA, or amplifier to be used does not provide phantom power on the microphone inputs.

The Superlux PS2B is lightweight, compact and portable, making it ideal for indoor or outdoor applications. It is well suited for live sound, stage or home studio venues when using condenser microphones and compact mixers. It features large rubber bumper guards to decrease vibration and also serve as stacking feet.

The Superlux PS2B is powered by two 9 volt alkaline batteries or suitable AC power supply. The PS2B has 2 balanced XLR microphone inputs and 2 balanced XLR microphone outputs. It provides clean phantom power for one or two microphones.

Different condenser microphones have different power needs. The PS2B features a 3-way selector switch that allows you to select between 12 volts and 48 volts of phantom power and has an off position to conserve battery life.

The Superlux PS2B is ruggedly constructed and operates with extremely low noise. It is a perfect solution for applications where the use of condenser microphones is desired and the mixer, recorder, PA, or amplifier to be used does not provide phantom power on the microphone inputs.

SPECIFICATIONS

Input connectors	2 x XLRF
Output connectors	2 x XLRM
Power supply	2 x 9V batteries (supplied) or suitable 12V DC power supply (not supplied)
Voltage Output	Selectable 12V or 48V
Dimensions (with foot pads)	6.1" x 4.3" x 2.2"
Weight	22.9 ounces