



Configuration:

LA-490-BK-W9 – Worldwide Use

Product Overview:

The LA-490 Listen Bluetooth/IR Beacons are small wall-mounted units that create a fully automated experience for venues using ListenWIFI. By transmitting a Bluetooth and/or Infrared signal, they help mobile apps and receivers determine relative location or proximity. Beacons enable automatic delivery of the correct audio channel to listeners based on their physical location, eliminating the need for manual channel selection or QR code scanning. Beacons allow venues to seamlessly provide the right audio at the right place, even in the users preferred audio language for multi-lingual applications. The beacon is an ideal accessory for applications with 2 or more channels.

Highlights:

- Fully automates the user’s experience
- Enables automatic channel selection on user devices
- Supports both ListenWIFI mobile apps and [LWR-1050](#) Wi-Fi Audio Receivers
- Small size and light weight
- Bluetooth and IR triggering in one device
- Adjustable power and interval
- Battery or USB powered
- Easily mount on a wall or attach to an electrical box
- Simple to program and install using ListenWIFI Manager software (Windows®)
- Secure and tamper proof

Includes:

One (1) LA-490 Bluetooth/IR Beacon Two (2) AA Alkaline Batteries One (1) USB Power Supply One (1) Mounting Hardware One (1) Oversized Wall Plate One (1) Quick Start Guide

Product Specification: LA-490 Listen Bluetooth/IR Beacon (COMING SOON)	
Physical	
Dimensions (H x W x D) with Mounting Plate	11.7 x 7.6 x 2.5 cm (4.6 x 3.0 W x 1.0 in.)
Unit Dimensions (H x W x D)	11.4 x 7.1 x 2.3 cm (4.5 x 2.8 W x 0.9 in.)
Unit Weight with batteries	143 g (5.0 oz.)
Unit Weight	76 g (2.7 oz.)
Shipping Weight	430 g (15.2 oz.)
Enclosure/Mounting Materials	PC plastic (IR transparent)
LED	Multi-colored, multi-function
Color	Dark Grey, chrome logo

Product Specification: LA-490 Listen Bluetooth/IR Beacon (COMING SOON)	
USB Connection	USB-Micro for power and programming
Mounting Hardware	Mounts to wall or single gang electrical box (US and European), tamper proof hex screw
Oversized Wall Plate	Fits standard US and European single gang electrical box
Battery Door	Removable for battery replacement
Communications	
Bluetooth (BT)	5.0, Bluetooth Low Energy (BLE), for programming and audio triggering
Infrared (IR)	Infrared light used for audio triggering
Protocols	iBeacon, SyncLink
USB	2.0
Security	PIN-protected for tamper-proof operation, restricted to authorized software only (OTA).
Range	
Bluetooth	To be published
Infrared	To be published
Controls	
User Controls	Bluetooth triggering, Bluetooth power, Infrared triggering, Infrared power, transmit interval, LED indicators, low battery LED, OTA configuration, trigger ID, UUID, firmware updates, reset to defaults
Setup/Programming	Programming via USB connection or Bluetooth OTA connection with ListenWiFi Manager software. The ListenWiFi Manager provides central management of the entire ListenWiFi system, including Beacons.
Indicators	
LED	Blue flash every 5 seconds indicates normal operation (can be disabled); Red flashing every 5 seconds indicates low battery (can be disabled); Green flash every second indicates active Bluetooth OTA connection with ListenWiFi Manager software; Alternating Amber/Red indicates beacon is performing a firmware upgrade
Power & Battery Life	
Power Supply	USB-Micro - 5V, 500mA
Battery Type	Alkaline batteries, non-rechargeable, field replaceable
Battery Size	AA
Battery Life	To be published
	*Dependent upon device configuration and batteries. Recommend powering via USB for Infrared mode.
Environmental	
Temperature - Operation	-10 °C (14 °F) to +40 °C (104 °F)
Temperature - Storage	-20 °C (-4 °F) to +50 °C (122 °F)
Relative Humidity	0 to 95% relative humidity, non condensing
Compliance	
Regulatory Marks	FCC, CE, ROHS, UKCA
Warranty	

Product Specification: LA-490 Listen Bluetooth/IR Beacon (COMING SOON)	
Beacon Warranty	1 year
*Specifications are subject to change without notice	