

ADJ UBL6H - DMX TRAITS

CHANNEL							DMX VALUES	FUNCTION
6Ch	11Ch	13Ch	16Ch	18Ch	25Ch	28Ch		
1	1	1	1				000 - 255	All Red , 0% to 100%
2	2	2	2				000 - 255	All Green , 0% to 100%
3	3	3	3				000 - 255	All Blue , 0% to 100%
4	4	4	4				000 - 255	All Amber , 0% to 100%
5	5	5	5				000 - 255	All Lime , 0% to 100%
6	6	6	6				000 - 255	All UV , 0% to 100%
				1	1	1	000 - 255	Red 1 , 0% to 100%
				2	2	2	000 - 255	Green 1 , 0% to 100%
				3	3	3	000 - 255	Blue 1 , 0% to 100%
				4	4	4	000 - 255	Amber1 , 0% to 100%
				5	5	5	000 - 255	Lime 1 , 0% to 100%
				6	6	6	000 - 255	UV 1 , 0% to 100%
				7	7	7	000 - 255	Red 2 , 0% to 100%
				8	8	8	000 - 255	Green 2 , 0% to 100%
				9	9	9	000 - 255	Blue 2 , 0% to 100%
				10	10	10	000 - 255	Amber 2 , 0% to 100%
				11	11	11	000 - 255	Lime 2 , 0% to 100%
				12	12	12	000 - 255	UV 2 , 0% to 100%
				13	13	13	000 - 255	Red 3 , 0% to 100%
				14	14	14	000 - 255	Green 3 , 0% to 100%
				15	15	15	000 - 255	Blue 3 , 0% to 100%
				16	16	16	000 - 255	Amber 3 , 0% to 100%
				17	17	17	000 - 255	Lime 3 , 0% to 100%
				18	18	18	000 - 255	UV 3 , 0% to 100%
	7	7	7		19	19	000 - 255	Color Macros , see Color Macros Chart section of this manual
	8	8	8		20	20	000 - 255	Color Temperature , 2300K - 9900K Linear
								Color Temperature Presets
							000 - 010	No Function
							011 - 026	2300K
							027 - 043	2700K
							044 - 060	3000K
							061 - 076	3200K
							077 - 093	4000K
							094 - 110	4500K
							111 - 126	5000K
							127 - 143	5600K
							144 - 160	6500K
	9	9	9		21	21		

CONTINUED ON NEXT PAGE

ADJ UBL6H - DMX TRAITS

CHANNEL							DMX VALUES	FUNCTION
6Ch	11Ch	13Ch	16Ch	18Ch	25Ch	28Ch		
								<i>Color Temperature Presets (continued)</i>
	9	9	9		21	21	161 - 176	7000K
							177 - 193	7500K
							194 - 210	8000K
							211 - 226	8500K
							227 - 255	9900K
								<i>Shutter / Strobe</i>
							000 - 031	LEDs Off
							032 - 063	LEDs On
							064 - 095	Strobe Effect, slow to fast
	10	10	10		22	22	096 - 127	LEDs On
							128 - 159	Pulse Effect in Sequences
							160 - 191	LEDs On
							192 - 223	Random Strobe Effect, slow to fast
							224 - 255	LEDs On
	11	11	11		23	23	000 - 255	<i>Dimmer Intensity</i> , 0% to 100%
								<i>Auto Programs</i>
							000 - 010	Off
							011 - 026	Program 1
							027 - 043	Program 2
							044 - 060	Program 3
							061 - 076	Program 4
							077 - 093	Program 5
			12			24	094 - 110	Program 6
							111 - 126	Program 7
							127 - 143	Program 8
							144 - 160	Program 9
							161 - 176	Program 10
							177 - 193	Program 11
							194 - 210	Program 12
							211 - 226	Program 13
							227 - 255	No Function
			13			25	000 - 255	<i>Auto Program Speed</i> , slow to fast
			14			26	000 - 255	<i>Auto Program Fade</i> , 0% to 100%

CONTINUED ON NEXT PAGE

ADJ UBL6H - DMX TRAITS

CHANNEL							DMX VALUES	FUNCTION
6Ch	11Ch	13Ch	16Ch	18Ch	25Ch	28Ch		
		12	15		24	27		<i>Dim Mode</i>
							000 - 020	Default to Unit Setting
							021 - 040	Standard
							041 - 060	Stage
							061 - 080	TV
							081 - 100	Architectural
							101 - 120	Theatre
							121 - 140	Stage 2
							140 - 160	Dim Speed, fast to slow (0.1s to 10s)
							161 - 255	Default to Unit Setting
		13	16		25	28		<i>Dim Curves</i>
							000 - 020	Square
							021 - 040	Linear
							041 - 060	Inv. Squa
							061 - 080	S. Curve
							081 - 255	No Function