

RELATION SIXPAR 200IP & WMG - DMX TRAITS

6Ch	7Ch	8Ch	12Ch	DMX Values	Function
1	1	1	1		Red
				0 - 255	0 - 100%
2	2	2	2		Green
				0 - 255	0 - 100%
3	3	3	3		Blue
				0 - 255	0 - 100%
4	4	4	4		White
				0 - 255	0 - 100%
5	5	5	5		Amber
				0 - 255	0 - 100%
6	6	6	6		UV
				0 - 255	0 - 100%
	7	7	7		Dimmer
				0 - 255	0 - 100%
		8	8		Strobe
				0 - 31	LED Off
				32 - 63	LED On
				64 - 95	Normal strobe, slow to fast
				96 - 127	LED On
				128 - 159	Pulse strobe rate, slow to fast
				160 - 191	LED On
				192 - 223	Random strobe rate, slow to fast
224 - 255	LED On				
			9		Static Color
				0 - 255	See Static Color Table
			10		Programs
				0 - 20	No function
				21 - 40	30 Color Jump
				41 - 60	Jump Change 6 Colors
				61 - 80	Fantasy 15 Colors
				81 - 255	Black Field
			11		Program Speed
				0 - 255	Speed adjustment
			12		Dimming Mode
				0 - 20	Standard
				21 - 40	Stage
				41 - 60	TV
				61 - 80	Architectural
				81 - 100	Theatre
				101 - 255	Dimming Mode Determined by Display