

ELIMINATOR MDF3 - DMX TRAITS

Channel				Value	Function
CH03	CH05	CH07	CH10		
1	1	1	1	000 - 255	Red LEDs , 0% - 100%
2	2	2	2	000 - 255	Green LEDs , 0% - 100%
3	3	3	3	000 - 255	Blue LEDs , 0% - 100%
					Color Macros
		4	4	000	No effect
				001 - 255	32 Color Macros, see Color Macros section of this manual for info
					Strobe
				000 - 031	Off
				032 - 063	On
				064 - 095	Variable Strobe, slow to fast
		5	5	096 - 127	On
				128 - 159	Strobe Pulse Effect, slow to fast
				160 - 191	On
				192 - 223	Random Strobe, slow to fast
				224 - 255	On
	4	6	6	000 - 255	Master Dimmer , 0% to 100%
	5	7	7	000 - 255	Master Dimmer Fine
			8	000 - 255	Dimming Speed , fast to slow
					Internal Programs
				000 - 010	Maintain
				011 - 060	Random Color Change
			9	061 - 110	Color Jump
				111 - 160	Color Gradient
				161 - 210	Color Pulse
				211 - 255	Sound Control
			10	000 - 255	Color Change Speed Control , slow to fast - OR - Sound Sensitivity , least to most sensitive