

ELIMINATOR MEGA BAR RGBA EP - DMX TRAITS

CHANNEL							DMX VALUES	FUNCTION
4 CH	6 CH	7CH	9 CH	10 CH	18 CH	34 CH		
1	1	1	1				000 - 255	Red , dim to bright
2	2	2	2				000 - 255	Green , dim to bright
3	3	3	3				000 - 255	Blue , dim to bright
4	4	4	4				000 - 255	Amber , dim to bright
				1			000 - 255	Red 1-4 , dim to bright
				2			000 - 255	Green 1-4 , dim to bright
				3			000 - 255	Blue 1-4 , dim to bright
				4			000 - 255	Amber 1-4 , dim to bright
				5			000 - 255	Red 5-8 , dim to bright
				6			000 - 255	Green 5-8 , dim to bright
				7			000 - 255	Blue 5-8 , dim to bright
				8			000 - 255	Amber 5-8 , dim to bright
					1		000 - 255	Red 1 & 2 , dim to bright
					2		000 - 255	Green 1 & 2 , dim to bright
					3		000 - 255	Blue 1 & 2 , dim to bright
					4		000 - 255	Amber 1 & 2 , dim to bright
					5		000 - 255	Red 3 & 4 , dim to bright
					6		000 - 255	Green 3 & 4 , dim to bright
					7		000 - 255	Blue 3 & 4 , dim to bright
					8		000 - 255	Amber 3 & 4 , dim to bright
					9		000 - 255	Red 5 & 6 , dim to bright
					10		000 - 255	Green 5 & 6 , dim to bright
					11		000 - 255	Blue 5 & 6 , dim to bright
					12		000 - 255	Amber 5 & 6 , dim to bright
					13		000 - 255	Red 7 & 8 , dim to bright
					14		000 - 255	Green 7 & 8 , dim to bright
					15		000 - 255	Blue 7 & 8 , dim to bright
					16		000 - 255	Amber 7 & 8 , dim to bright
						1	000 - 255	Red 1 , dim to bright
						2	000 - 255	Green 1 , dim to bright
						3	000 - 255	Blue 1 , dim to bright
						4	000 - 255	Amber 1 , dim to bright
						5	000 - 255	Red 2 , dim to bright
						6	000 - 255	Green 2 , dim to bright
						7	000 - 255	Blue 2 , dim to bright
						8	000 - 255	Amber 2 , dim to bright
						9	000 - 255	Red 3 , dim to bright

CONTINUED ON NEXT PAGE

ELIMINATOR MEGA BAR RGBA EP - DMX TRAITS

CHANNEL							DMX VALUES	FUNCTION
4 CH	6 CH	7 CH	9 CH	10 CH	18 CH	34 CH		
						10	000 - 255	Green 3 , dim to bright
						11	000 - 255	Blue 3 , dim to bright
						12	000 - 255	Amber 3 , dim to bright
						13	000 - 255	Red 4 , dim to bright
						14	000 - 255	Green 4 , dim to bright
						15	000 - 255	Blue 4 , dim to bright
						16	000 - 255	Amber 4 , dim to bright
						17	000 - 255	Red 5 , dim to bright
						18	000 - 255	Green 5 , dim to bright
						19	000 - 255	Blue 5 , dim to bright
						20	000 - 255	Amber 5 , dim to bright
						21	000 - 255	Red 6 , dim to bright
						22	000 - 255	Green 6 , dim to bright
						23	000 - 255	Blue 6 , dim to bright
						24	000 - 255	Amber 6 , dim to bright
						25	000 - 255	Red 7 , dim to bright
						26	000 - 255	Green 7 , dim to bright
						27	000 - 255	Blue 7 , dim to bright
						28	000 - 255	Amber 7 , dim to bright
						29	000 - 255	Red 8 , dim to bright
						30	000 - 255	Green 8 , dim to bright
						31	000 - 255	Blue 8 , dim to bright
						32	000 - 255	Amber 8 , dim to bright
		5	5				000 - 255	Color Macros , refer to Color Macros Table section of this manual
								Programs
							000 - 015	No function
							016 - 025	Program 1
							026 - 035	Program 2
							036 - 045	Program 3
							046 - 055	Program 4
							056 - 065	Program 5
							066 - 075	Program 6
							076 - 085	Program 7
							086 - 095	Program 8
							096 - 105	Program 9

CONTINUED ON NEXT PAGE

ELIMINATOR MEGA BAR RGBA EP - DMX TRAITS

CHANNEL							DMX VALUES	FUNCTION	
4 CH	6 CH	7 CH	9 CH	10 CH	18 CH	34 CH			
			6					<i>Programs (continued)</i>	
								106 - 115	Program 10
								116 - 125	Program 11
								126 - 135	Program 12
								136 - 145	Program 13
								146 - 155	Program 14
								156 - 165	Program 15
								166 - 175	Program 16
								176 - 185	Program 17
								186 - 195	Program 18
								196 - 205	Program 19
								206 - 215	Program 20
								216 - 225	Program 21
								226 - 235	Program 22
							236 - 245	Auto Run	
							246 - 255	Sound Active	
			7					<i>Program Speed/Sound Sensitivity</i>	
								000 - 255	Program speed, slow to fast
								000 - 255	Sound sensitivity, least to most
	5	6	8	9	17	33		<i>Strobe</i>	
							000 - 007	No function	
							008 - 255	Strobe speed, slow to fast	
	6	7	9	10	18	34	000 - 255	<i>Dimmer</i> , dim to bright	