



**Product Overview:**

Designed to mount to the rear BNC antenna connector, the LA-124 antenna offers an outstanding coverage range up to 198m (650 ft.). The 90-degree antenna is compatible with the 216 MHz versions of our LT-800 transmitter, LR-100 receiver/amplifier, and the LR-600 receiver/speaker. The LA-124 can also be used to create a custom, remote antenna, such as a wall plate-mounted antenna.

**Highlights:**

- Mounts with a BNC connector
- Compatible with 216 MHz equipment including our LT-800 transmitter and LR-100 receiver
- Range up to 183 m / 600 ft.

**Includes:**

One (1) LA-124 90° Helical Antenna (216 MHz)

Product Specification: 90 Degree Helical Antenna (216 MHz)	
<b>Interconnections</b>	
Connector/s	BNC
<b>RF</b>	
Frequency Range	216.025 - 216.950 MHz
Number of Channels	57 (19 wide, 38 narrow)
Typical Range	Range up to 183 m / 600 ft.
<b>Physical</b>	
Length	4.5 in. (11.4 cm)
Color	Dark Gray
Shipping Weight	1 lb. (0.5 kg)
Diameter	0.44 in. (1.10 cm)
Weight	1 oz. (28 g)