



INGENIA STA-IG FLYBAR ANGLES CONFIGURATIONS

Pick Point Position	Speaker configuration (STA-IG + Ingenia series)							
	1 x IG1T	2 x IG1T	1 x IG2T	2 x IG2T	1 x IG3T	2 x IG3T	1 x IG4T	2 x IG4T
	Vertical axis values (degrees°)							
14	-31,20	-18,50	-25,20	-14,80	-22,30	-13,40	-20,80	-12,40
13	-28,70	-16,60	-22,40	-12,70	-20,00	-12,00	-18,90	-11,10
12	-25,80	-15,50	-19,50	-11,40	-17,90	-10,60	-16,90	-10,30
11	-22,60	-13,10	-16,70	-9,80	-15,40	-9,10	-14,10	-9,00
10	-19,30	-11,00	-13,50	-8,00	-12,70	-7,80	-12,70	-7,70
9	-16,00	-9,10	-10,60	-6,20	-10,70	-6,10	-10,20	-6,50
8	-11,50	-5,90	-6,40	-3,40	-7,00	-3,90	-7,50	-4,30
7	-6,50	-3,70	-2,80	-0,80	-3,70	-1,50	-4,70	-2,20
6	-2,40	-1,30	+0,00	+0,80	-1,20	+0,00	-1,70	-0,40
5	+0,30	+1,10	+4,10	+2,90	+1,40	+1,40	+0,80	+0,90
4	+5,20	+4,10	+7,50	+4,50	+4,50	+3,10	+3,00	+2,20
3	+8,80	+5,50	+11,00	+6,80	+7,80	+4,80	+5,50	+3,40
2	+13,50	+7,20	+14,30	+8,40	+10,90	+6,10	+7,50	+4,50
1	+17,40	+9,60	+17,10	+10,20	+12,10	+7,50	+9,30	+6,20

